

# User Guide


## DP-10

Digital Earth Leakage Relay

### features

- True RMS Measurement with SPARC<sup>1</sup> and DCO<sup>2</sup> Algorithm
- Fundamental Signal Detection<sup>3</sup>
- Real Time Display of  $I_{\Delta n}$  in mA/A
- Fault / lo-set & hi-set Trip LED Indication
- Fault Start Event Recording & LED Indication + Output<sup>4</sup>
- Pre-Alarm LED Indication + Output<sup>4</sup>
- Trip Event Memory (non-volatile 7 previous records)
- Fault Start Event Memory (non-volatile 4 previous records)
- Selectable Frequency (50 / 60 Hz)
- Programmable Relay Output contact for K2
- Last Trip Elapsed Time (up to 99days)
- Auto Z.C.T. detection
- Software Lock to Prevent Unauthorized Setting
- Complies with IEC-60255-26/27 ; BS EN 50121-5 Standards
- External Plug-in Module for :- A-01s / A-01sp (RS-485 MODBUS RTU) isolated type

### Panel Overview



- a. Single digit mode LED display
- b. 3 digit data LED display
- c. (mA) indication
- d. Pre-Alarm output indication
- e. Fault start indication
- f. Hi-set trip indication
- g. Fault indication
- h. Lo-set trip indication
- i. Up button / Increment
- j. Mode select / Set button
- k. Reset / Undo / Test trip button
- l. Down button / Decrement


### Technical Data

Aux Power	: 65 ~ 275 Vac (45 ~ 65 Hz); 90 ~ 300 Vdc (for model 220a)
	: 18 ~ 72 Vdc (for model 024d)
Fundamental Frequency	: 50 or 60 Hz (software selectable)
Current Input ( $I_{\Delta n}$ )	: ZCT (multiple sizes from ID of 30~300mm)
Measurement Range	: 0.01 ~ 30.0 A
Output Relay Rating	: SPDT 5A, 250V AC/DC
Consumption	: < 3 VA
Accuracy	: Current protection threshold ( $\pm 5\%$ ), Time delayed (+5% or 50ms)
Display	: 7-Segment LED (3 + 1 digit)
Indication (LEDs)	: mA, pre-alarm, fault start event, lo / hi-set trip, fault
Operating Temp.	: 0°C ~ +55°C
Humidity	: 56 days at 93%RH, 40°C non-condensing
IP Rating	: IP54 (front panel)
Weight	: 230 g

### Parameter Setting Range

$I_{\Delta n} > (A)$ : lo-set trip	0.03 ~ 1.00 A (step of 0.01 A)
<b>0.03 ~ 30.0 A</b>	1.00 ~ 3.00 A (step of 0.05 A)
	3.00 ~ 10.0 A (step of 0.10 A)
	10.0 ~ 30.0 A (step of 0.50 A)
$t > (sec)$ : lo-set trip time delay	0.03 ~ 0.10 s (step of 0.01s)
<b>0.03 ~ 20.0 s</b>	0.10 ~ 1.00 s (step of 0.02s)
	1.0 ~ 20.0 s (step of 0.1s)
$I_{\Delta n} \gg (A)$ : hi-set trip	0.10 ~ 10.0 A (step of 0.10 A)
<b>OFF or 0.10 ~ 30.0 A</b>	10.0 ~ 30.0 A (step of 0.50 A)
$t \gg (sec)$ : hi-set trip time delay	<b>fixed @ 30ms</b>

### Casing



Panel Cut-out  
92 x 92


Note: All measurement in mm.

Note: Specification subject to change without prior notification (please visit [www.delab.com.my](http://www.delab.com.my) for latest specification)

YouTube : Delab Scientific Sdn. Bhd.



### Wiring





## Modes



0.50	<b>1</b> I <sub>Δn</sub> > (A)	lo-set leakage current
0.30	<b>2</b> t > (sec)	Trip time delay
OFF	<b>3</b> I <sub>Δn</sub> >> (A)	hi-set leakage current

<b>5</b> , <b>6</b> <b>1</b> to <b>6</b> <b>6</b>	Trip memory	7 trip event memories (non-volatile)
<b>d</b>	Last trip elapsed time	Last trip elapsed time
<b>1</b> to <b>4</b> <b>4</b>	Fault start memory	4 fault start event memories (non-volatile)
<b>U</b> <b>E</b> <b>r</b>	Version	Firmware version
<b>o</b> <b>P</b> <b>h</b>	Operation hours	Device operated in hours (x 1000 hr)

OFF	<b>4</b>	Software lock	: Keypad lock : OFF or ON
Lc	<b>1</b> <b>1</b>	Trip relay K1 response type	: Latching (Lc) or Non-latching (nLc)
trP	<b>2</b> <b>2</b>	Output relay K2 function	: Programmable relay output
nLc	<b>2</b> <b>2</b>	Trip relay K2 response type	: Latching (Lc) or Non-latching (nLc)
50	<b>2</b> <b>2</b>	Network frequency	: Selectable as : 50 Hz or 60 Hz
On	<b>2</b>	Standby mode	: Running LED bar : ON or OFF
Aut	<b>6</b> <b>6</b>	Z.C.T. detection	: Auto detection or no detection
non	<b>2</b> <b>2</b>	Selection of plug-in module	: A-01s / A-01sp (RS485 modbus isolated type) or none
1	<b>2</b> <b>2</b>	Modbus address	: Selectable from 1 ~ 247
96	<b>6</b> <b>6</b>	Baud rate setting	: Selectable from 3, 6, 12, 24, 48, 96, 192, 288
non	<b>2</b> <b>2</b>	Parity setting	: Selectable: None or Odd or Even
	<b>End</b>	End program setting	: Save Changes and exit setting mode

## Parameters Setting

### **1** I<sub>Δn</sub> > (A) : To set lo-set leakage current

- Step 1: Press [ SELECT ] button once to enter mode **1**.  
Display will show the existing set value. (Range : 0.03 ~ 30.0 Ampere)
- Step 2: Set the desired lo-set leakage current using the [ Up ] or [ Down ] button.  
Newly selected value will flash.
- Step 3: Press [ SELECT ] button to store / confirm new value and advance to mode **2** or press [ UNDO ] button to undo changes.

### **2** t > (sec) : To set trip time delay

- Step 1: Press [ SELECT ] button until mode **2** is displayed.  
Display will show the existing set value. (Range : 0.03 ~ 20.0 seconds)
- Step 2: Set the desired trip time using the [ Up ] or [ Down ] button.  
Newly selected value will flash.
- Step 3: Press [ SELECT ] button to store / confirm new value and advance to mode **3** or press [ UNDO ] button to undo changes.

### **3** I<sub>Δn</sub> >> (A) : To set hi-set leakage current

- Step 1: Press [ SELECT ] button until mode **3** is displayed.  
Display will show the existing set value. (Range : OFF or 0.10 ~ 30.0 Ampere)
- Step 2: Set the desired hi-set leakage current using the [ Up ] or [ Down ] button.  
Newly selected value will flash.
- Step 3: Press [ SELECT ] button to store / confirm new value and advance to mode **6** or press [ UNDO ] button to undo changes.



## Info Viewing

### **5**, **6** **1** ~ **6** **6** Tripped values for last 7 events

Press [ SELECT ] button until mode **5**.  
Display will flash the tripped value for the most recent tripped event.

Single flash	: Indicate a lo-set trip	To reset trip event memory, hold [RESET] button for 3 sec. in mode <b>5</b> .
Double flash	: Indicate a high-set trip	

Manual tripped event will display a flashing **E r P**.  
If display shows **---**. (No tripping has occurred)  
Press [ SELECT ] button again to scroll thru mode **6** **1** to **6** **6**. (Auto skip to mode **6** if memory is empty)  
To skip directly to mode **5**, hold [ SELECT ] button for 1 sec.  
To exit, press [ UNDO ] button.

### **d** View last trip elapsed time

Press [ SELECT ] button until mode **d**.  
Display will show **---** (device has no tripping since last power up).



To exit, press [ UNDO ] button.

### **1** ~ **4** Fault start event memory

Press [ SELECT ] button until mode **1**. If display show **---** (no fault event has occurred).  
Press [ SELECT ] button again to scroll thru mode **2** to **4**. (Auto skip to mode **1** if memory is empty)  
To reset memory, hold [ RESET ] button for 3 seconds in mode **1**.  
To exit, press [ UNDO ] button.

### **U** **E** **r** Firmware version

This mode is not adjustable. For user to view firmware version.  
Press [ SELECT ] button until mode **U E r** is being displayed.  
The display will show the firmware version of the device.  
To exit, press [ UNDO ] button.

### **o** **P** **h** Total operation hour

This mode shows the total time of the device that has been in operation.  
Press [ SELECT ] button until mode **o P h** is being displayed.  
Display will show a value (x1000 hr).  
To exit, press [ UNDO ] button.



## Special Setting Modes

When no mode is selected (mode display is blank)



Press 'SELECT & RESET' button simultaneously & hold for 5 seconds until mode **5** appears



Press 'UP or Down' button to modify parameters



Press 'SET' button to confirm & proceed to next mode

### **L** Software keypad lock

**OFF** or **ON**

### **F** **r** Electrical network system frequency

Electrical network frequency setting:  
**50** = 50 Hz **60** = 60 Hz

### **1** **1** Trip relay K1 response type

**Lc** : Latching trip **nLc** : Non-Latching trip

### **-** Standby option

**OFF** : De-activate **ON** : Activate

After about 3 minutes of idle and no leakage is detected, running LED bar will be displayed instead of the real time leakage current if activated. It automatically exits on leakage detection or Z.C.T. is not connected or when any button is pressed. When device trips, standby mode is temporary de-activated until device is reset.

### **1** **2** Output relay K2 function

**Lc P** : Tripping output (Lc / nLc)

### Fault Start Output Function

**LFS** : Lo-set fault start signal output (Lc / nLc)  
**HFS** : Hi-set fault start signal output (Lc / nLc)  
**AFS** : Any fault start signal output (Lc / nLc)

Fault start event LED (e) indicates any detected fault events.

To clear event indication, press [RESET] button or scroll to mode **1** **1** while no fault is present. K2 output will be on if programmed as fault start event. To latch fault events output, select **1** **2** to Lc in trip relay K2 response type.

### Device Failure Output Function

**OFF** : Device failure output (nLc only)

K2 automatically turns ON when device and Z.C.T. are functioning normally.

K2 will turns OFF when device is malfunction or Z.C.T. is open-circuited.

### Circuit Breaker Failure Output Function

**Lc P** : Circuit breaker failure output (nLc only)  
Activates K2 output if fault still exists after 100 ms of trip event.

### Pre-Alarm Output Function

**A50** : >50% of I<sub>Δn</sub> > (Lc / nLc)  
**A90** : >90% of I<sub>Δn</sub> > (Lc / nLc)

If K2 is programmed to pre-alarm [A50 or A90]. Pre-alarm output LED (d) will indicate the status of K2. Set **1** **2** to Lc in trip relay K2 response type if need to latch pre-alarm events.  
Press [ RESET ] button to clear output.

### **1** **2** Trip relay K2 response type

**Lc** : Latching trip **nLc** : Non-Latching trip

### **6** **6** Z.C.T. detection

**OFF** : No detection **Aut** : Auto detection

**2** **6** is being displayed and flashing instead of the real time leakage current when auto Z.C.T. detection is activated, it means that the Z.C.T. is not connected properly. User may need to check the wiring connection with the device.

### **1** **2** Selection of plug-in module

**1** **2** : A-01s / A-01sp **non** : None

### **1** **2** Modbus address

Selectable from 1~247

### **6** **6** Baud rate setting

Set the baud rate in a modbus communication between host computer and device. Selectable as: (3 = 300, 6 = 600, 12 = 1200, 24 = 2400, 48 = 4800, 96 = 9600, 192 = 19200 or 288 = 28800 ) bps

### **1** **2** Parity setting

**non** : None **Odd** : Odd **Even** : Even

Set the parity for Modbus communication between host computer and the unit.

### **End** End setting

Press [ SELECT ] button to exit and save the setting or [ UNDO ] button to go back.